

# BASSI LABS GECI RED DIAMOND PROGRAMMING



## Red Diamond Charger Programming

*This guide will take you through the steps to properly enter the GECI GREEN or BLACK Diamond charger's programming in the event where you need to modify the charger's settings.*

### STEP 1: ENTERING THE SETTINGS

To enter the settings you will need to enter the password prompt by pressing the RIGHT button for 3 seconds.



### STEP 2: ENTERING THE PASSWORD

On the GECI RED Diamond the password will vary depending whether you are trying to enter USER or MANUFACTURER mode

TIME	USER PASSWORD	MANUFACTURER
0h00 to 4h00	LF-LF-LF-LF	CN-CN-CN-CN

LF = LEFT BUTTON      CN= CENTER BUTTON

### STEP 3: ENTERING ADMIN MODE

If you wish to enter the admin mode you will need to first enter MANUFACTURER mode. Make your way to the time setting using the right or left button. Hold the middle button for 3 seconds or until the display cursor blinks. Repeat the holding process until the cursor is set on the hours.

Then, set the time to 10:00 using the left or right arrow to go up and down. Hold the middle button once again for 3 seconds to reach the minutes and then once more so that you no longer see the blinking LED.

Cycle the charger OFF and ON and reach the password prompt and enter the following password.

**CN-LF-LF-CN**

Don't forget to set the time back to the current time once you are done.

